

Female Connector

Order Number	Outer Diameter	size			
		A	D	E	F
Female Connector					
Inch					
SS-FC-2-2	1/8"X1/8"	1.13			9/16
SS-FC-2-4	1/8"X1/4"	1.32	0.50	0.09	3/4
SS-FC-3-2	3/16"X1/8"	1.17	0.54	0.12	9/16
SS-FC-4-2	1/4"X1/8"	1.23			9/16
SS-FC-4-4	1/4"X1/4"	1.41	0.60	0.19	3/4
SS-FC-4-6	1/4"X3/8"	1.48			7/8
SS-FC-4-8	1/4"X1/2"	1.67			1 1/16
SS-FC-5-2	5/16"X1/8"	1.26	0.64	0.25	9/16
SS-FC-5-4	5/16"X1/4"	1.45			3/4
SS-FC-6-2	3/8"X1/8"	1.29			5/8
SS-FC-6-4	3/8"X1/4"	1.48	0.66	0.28	3/4
SS-FC-6-6	3/8"X3/8"	1.54			7/8
SS-FC-6-8	3/8"X1/2"	1.73			1 1/16
SS-FC-6-12	3/8"X3/4"	1.88			1 5/16
SS-FC-8-4	1/2"X1/4"	1.59	0.90	0.41	13/16
SS-FC-8-6	1/2"X3/8"	1.65			7/8
SS-FC-8-8	1/2"X1/2"	1.84			1 1/16
SS-FC-8-12	1/2"X3/4"	1.90			1 5/16
SS-FC-10-6	5/8"X3/8"	1.65	0.96	0.50	15/16
SS-FC-10-8	5/8"X1/2"	1.84			1 1/16
SS-FC-10-12	5/8"X3/4"	1.90			1 5/16
SS-FC-12-8	3/4"X1/2"	1.84	0.96	0.62	1 1/16
SS-FC-12-12	3/4"X3/4"	1.90			1 5/16
SS-FC-14-12	7/8"X3/4"	1.96	1.02	0.72	1 5/16
SS-FC-16-12	1"X3/4"	2.10	1.23	0.88	1 3/8
SS-FC-16-16	1"X1"	2.45			1 5/8
Metric					
SS-FC-3M-2	3mmX1/8"	28.7	12.9	2.4	14
SS-FC-3M-4	3mmX1/4"	33.5			19
SS-FC-4M-2	4mmX1/8"	29.7	13.7	2.4	14
SS-FC-6M-2	6mmX1/8"	31.3			14
SS-FC-6M-4	6mmX1/4"	35.8	15.3	4.8	19
SS-FC-6M-6	6mmX3/8"	37.6			22
SS-FC-6M-8	6mmX1/2"	42.5			27
SS-FC-8M-2	8mmX1/8"	32.1			15
SS-FC-8M-4	8mmX1/4"	37.0	16.2	6.4	19
SS-FC-8M-6	8mmX3/8"	38.5			22
SS-FC-8M-8	8mmX1/2"	43.3			27
SS-FC-10M-4	10mmX1/4"	37.8	17.2	7.9	19
SS-FC-10M-6	10mmX3/8"	39.4			22
SS-FC-10M-8	10mmX1/2"	44.2			27
SS-FC-12M-4	12mmX1/4"	40.3	22.8	9.5	22
SS-FC-12M-6	12mmX3/8"	41.9			22
SS-FC-12M-8	12mmX1/2"	46.7			27
SS-FC-15M-8	15mmX1/2"	46.7	24.4	11.9	27
SS-FC-16M-8	16mmX1/2"	46.9	24.4	12.7	27
SS-FC-20M-8	20mmX1/2"	47.9	26.0	15.9	30
SS-FC-20M-12	20mmX3/4"	49.7			35
SS-FC-22M-12	22mmX3/4"	49.7	26.0	18.3	35
SS-FC-22M-16	22mmX1"	57.9			41
SS-FC-25M-12	25mmX3/4"	53.4	31.3	21.8	35
SS-FC-25M-16	25mmX1"	62.3			41

